


# ACP-IMX8-PI

Distributed by:



## Specification

### System Information

**Processor** 4xCortex-A53 core up to 1.8GHz per core  
1x Cortex-M4 core up to 400MHz

**System Memory** 4GB LPDDR4

**I/O Chipset** NXP iMX8M Mini

### Software Support

**OS** Yocto 4.0 (Linux)

### Storage

**Storage** 32GB eMMC5.1

### Ethernet

**Ethernet Interface** RJ45, 10/100/1000M

### I/O

**GPIO** 1x Standard 40-pin GPIO header  
( Can be expanded to UART, SPI, I2C, PWM function )

**USB** 1x4 pin USB-Wifi connector  
( Support USB-WiFi Module )

**Display** 1 x HDMI Out  
1 x HDMI Out 1x MIPI DSI  
( 2-lane MIPI DSI display port )

**Audio** 1 x 3.5mm Headphone Jack

Distributed by [www.texim-europe.com](http://www.texim-europe.com)

USB Port	4 x USB 2.0
Camera	1x MIPI CSI ( 2-lane MIPI CSI camera port )
SD	1 x SD
DC In / Out Connector	
Input Power Connector	USB Type C
DC In / Out Characteristics	
Working Voltage	DC 5V / 3A
Mechanical & Environmental	
Operating Temp.	-20°C ~ 70°C
Dimension (L x W)	85*56mm



## **Disclaimer**

ALL PRODUCTS, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE TO IMPROVE RELIABILITY, FUNCTION OR DESIGN OR OTHERWISE.

Texim Europe B.V. its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Texim"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product.

Texim makes no warranty, representation or guarantee regarding the suitability of the products for any particular purpose or the continuing production of any product.

It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application.

Parameters provided in datasheets and / or specifications may vary in different applications and performance may vary over time.

All operating parameters, including typical parameters, must be validated for each customer application by the customer's technical experts.

Please contact us if you have any questions about the contents of the datasheet.

This may not be the latest version of the datasheet. Please check with us if a later version is available.





## Headquarters & Warehouse

Elektrostraat 17  
NL-7483 PG Haaksbergen  
The Netherlands

T: +31 (0)53 573 33 33  
E: [info@texim-europe.com](mailto:info@texim-europe.com)  
Homepage: [www.texim-europe.com](http://www.texim-europe.com)



### The Netherlands

Elektrostraat 17  
NL-7483 PG Haaksbergen

T: +31 (0)53 573 33 33  
E: [nl@texim-europe.com](mailto:nl@texim-europe.com)



### Belgium

Zuiderlaan 14, box 10  
B-1731 Zellik

T: +32 (0)2 462 01 00  
E: [belgium@texim-europe.com](mailto:belgium@texim-europe.com)



### UK & Ireland

St Mary's House, Church Lane  
Carlton Le Moorland  
Lincoln LN5 9HS

T: +44 (0)1522 789 555  
E: [uk@texim-europe.com](mailto:uk@texim-europe.com)



### Germany

Bahnhofstrasse 92  
D-25451 Quickborn

T: +49 (0)4106 627 07-0  
E: [germany@texim-europe.com](mailto:germany@texim-europe.com)



### Germany

Martin-Kollar-Strasse 9  
D-81829 München

T: +49 (0)89 436 086-0  
E: [muenchen@texim-europe.com](mailto:muenchen@texim-europe.com)



### Austria

Warwitzstrasse 9  
A-5020 Salzburg

T: +43 (0)662 216 026  
E: [austria@texim-europe.com](mailto:austria@texim-europe.com)



### Nordic

Stockholmsgade 45  
2100 Copenhagen

T: +45 88 20 26 30  
E: [nordic@texim-europe.com](mailto:nordic@texim-europe.com)



### Italy

Martin-Kollar-Strasse 9  
D-81829 München

T: +49 (0)89 436 086-0  
E: [italy@texim-europe.com](mailto:italy@texim-europe.com)